

FEATURES

- Round, suspended architectural fixture adds visual interest to a variety of applications
- Sleek aircraft cable or pendant mount
- Provides soft, uniform ambient illumination
- Lift-and-twist lens assembly allows for easy maintenance
- Efficacies up to 143 lm/W
- Designed and manufactured in the USA

SPECIFICATIONS

- HOUSING .080" spun aluminum outer housing with C.R.S. back plate.
- SHIELDING Frosted acrylic lens, .125" thick
- FINISH Textured matte white polyester TGIC powder coat bonded to phosphate-free, multi-stage pretreated metal. All parts painted after fabrication to facilitate installation, increase efficiency, and inhibit corrosion.
- ELECTRICAL High quality mid-power LED boards. L85 at 50,000 hours. 25°C maximum ambient operating temperature.
- MOUNTING Suspended, Adjustable steel aircraft cable mounts to 1/4-20 stud provided by others; or use 3/8" IPS stem and canopy kit.
- LISTINGS cCSAus certified as luminaire suitable for dry or damp locations.
- WARRANTY 5-year limited warranty, see hew.com/warranty.

IMPORTANT: Electrostatic sensitive unit. Observe precautions when handling.

ORDERING EXAMPLE: RNDP - 4 - L200/835 - FXA - ACF*4P/D24 - OPTIONS - DIM - UNV

ORDERING INFO

SERIES	DIAMETER	LUMEN	IS ^[1]	CRI	CCT	LENS
RNDP	2 2'	2'		8 80	27 2700K	FXA Frosted convex acrylic lens
	3 3'	L25	2,500lm		30 3000K	
	4 4'	L45	4,500lm		35 3500K	
		L83	8,300lm		40 4000K	
		3'			50 5000K	
		L67	6,700lm			
		L150	15,000lm			
		4'				
		L136	13,600lm			
		L200	20,000lm			

MOUNTING AND POWER (EXAMPLE: ACF*4P/D24)[2]

Prefix	Fixture Size	Type	Length
ACF*	3P / 2' or 3' unit	D 1" grid & hardpan	24 24'
	4P/ 4' unit	N 9/16" grid	48 48'
		S Slot arid	96 96

OPTIONS

EM/10W REMOTE Remote mount emergency battery [4] Additional lower lumen packages available. Specify in increments of

100 nominal lumens. Example: 9,500 nominal lumens = RNDP-4-L136/835-FXA-(L95)

DRIVER [3]

DRV Non-dimming driver **DIM** Dimming driver DIM1 1% dimming driver

VOLTAGE

120 120V **277** 277V **UNV** 120-277V

NOTES

- Nominal lumen output based on 3500K CCT. Actual lumens may vary +/-5%, see page 2 for FIXTURE PERFORMANCE DATA.
- Additional lumen packages available, see options. See page 3 for MOUNTING DETAILS See page 3 for ADDITIONAL DRIVER OPTIONS.
- 120V Ž77V only. Requires remote mounted battery, provided with remote mounting enclosure for installation in ceiling above fixture. Separate power and control wiring to remote box required. See page 3 for REMOTE MOUNT DETAILS.



FIXTURE PERFORMANCE DATA

	LED PACKAGE	DELIVERED LUMENS	WATTAGE	EFFICACY (Im/W)
	L25	2528	24.3	104.1
2'	L45	4530	45.7	99.2
	L83	8195	85.0	96.4
2,	L67	6717	57.9	115.9
3'	L150	15019	136.3	110.9
4'	L136	13649	95.4	143.0
4	L200	20070	147.7	135.9


MULTIPLIER TABLES

COLOR TEMPERATURE			
ССТ	CONVERSION FACTOR		
2700K	097		
3000K	0.99		
3500K	1.00		
4000K	1.03		
5000K	1.06		

- Photometrics tested in accordance with IESNA LM-79. Results shown are based on 25°C ambient temperature.
- Wattage shown is average for 120V through 277V input.
- Results based on 3500K, 80 CRI, actual lumens may vary +/-5%
 Use multiplier table to calculate additional options.

PHOTOMETRY


RNDP-2-L83/835-FXA Total Luminaire Output: 8197 lumens; 85.0 Watts | Efficacy: 96.4 lm/W | 80.0 CRI; 3500K CCT



	VERTICAL ANGLE	HO	ZONAL LUMENS		
	VERTICAL ANGLE	0°	45°	90°	ZUNAL LUMENS
8	0	2844	2844	2844	
CANDLEPOWER DISTRIBUTION	5	2860	2840	2827	270
문	15	2764	2754	2744	776
S	25	2558	2548	2551	1178
2	35	2272	2265	2252	1416
M	45	1922	1876	1889	1457
Ĭ.	55	1463	1443	1453	1307
ᅙ	65	1004	1001	1004	992
5	75	555	559	539	584
	85	186	176	183	216
	90	76	83	86	

LUMEN SUMMARY	ZONE	LUMENS	% FIXTURE
Σ	0 - 30	2224	27
SU	0 - 40	3640	44
핕	0 - 60	6405	78
흨	0 - 90	8197	100
	0 - 180	8197	100


RNDP-3-L150/835-FXA Total Luminaire Output: 15114 lumens; 136.3 Watts | Efficacy: 110.9 lm/W | 80.0 CRI; 3500K CCT



	VEDTICAL ANGLE	НО	RIZONTAL ANG	GLE	ZONAL LUMENC
	VERTICAL ANGLE	0°	45°	90°	ZONAL LUMENS
8	0	5225	5225	5225	
DISTRIBUTION	5	5206	5202	5204	495
뭂	15	5034	5050	5050	1424
등	25	4684	4695	4689	2161
	35	4155	4146	4180	2602
8	45	3456	3490	3490	2690
CANDLEPOWER	55	2711	2704	2709	2418
를	65	1848	1871	1850	1841
S	75	988	1024	974	1061
	85	322	329	307	376
	90	123	129	120	

LUMEN SUMMARY	ZONE	LUMENS	% FIXTURE
Σ	0 - 30	4080	27
S	0 - 40	6682	44
핕	0 - 60	11790	78
≧	0 - 90	15068	100
	0 - 180	15114	100

RNDP-4-L200/835-FXA Total Luminaire Output: 20070 lumens; 147.7 Watts | Efficacy: 135.9 lm/W | 80.0 CRI; 3500K CCT




	VERTICAL ANGLE	НО	ZONAL LUMENS		
	VERTICAL ANGLE	0°	45°	90°	ZUNAL LUMENS
8	0	7356	7356	7356	
5	5	7102	7096	7090	678
물	15	6803	6794	6797	1924
CANDLEPOWER DISTRIBUTION	25	6157	6149	6154	2858
곮	35	5367	5357	5364	3388
8	45	4700	4691	4697	3574
굨	55	3598	3592	3604	3188
ᅙ	65	2477	2464	2480	2432
5	75	1313	1316	1316	1430
	85	467	475	475	547
	90	185	188	188	

LUMEN SUMMARY	ZONE	LUMENS	% FIXTURE
₹	0 - 30	5461	27
몽	0 - 40	8849	44
딟	0 - 60	15611	78
]	0 - 90	20019	100
	0 - 180	20070	100




CROSS-SECTION



FIXTURE SIZE	A (DIA.)	В	С
2'	ø26-3/16"	6-11/16"	5-1/8"
3'	ø36-11/16"	7-3/16"	5-1/8"
4'	ø48-11/16	7-11/16"	5-1/8"


MOUNTING DETAILS




4' MOUNTING INFORMATION ø24-1/2" for pendant mount ø23" for aircraft cable (2) ø7/8" KOs (4) ø3/4" KOs for pendant mount (4) 10-32 nuts

for aircraft


3' MOUNTING INFORMATION



EM/10W REMOTE MOUNT DETAILS



STANDARD MOUNTING HARDWARE



Fixtures are provided with:

- · Adjustable length aircraft cables, must specify
- White cord, No. 18 AWG
- One 5" and two or three 2" canopies
- T-bar clips with 1/4-20 stud
- Hard ceiling anchor provided by others
- The feeder kits are standard with a 5" canopy to cover the junction box and a 2" canopy at the non-feed point. No J-box is required at non-feed points.
- See instruction sheet for more information.

ADDITIONAL DRIVER OPTIONS

Note: Lumen restrictions apply, consult factory.

CATALOG NUMBER	DESCRIPTION
DRV	Driver prewired for non-dimming applications
DIM	Dimming driver prewired for 0-10V low voltage applications
DIM1	1% dimming driver prewired for 0-10V low voltage applications
DIM LINE	Line voltage dimming driver (Must specify 120V or 277V only)
SD40	40% step-dimming driver
SD50	50% step-dimming driver
DALI	DALI dimming driver
LTE LINE	Lutron Hi-lume® A-Series 1% dimming driver for forward phase line voltage controls (120V only)
LDE1	Lutron EcoSystem® H-Series 1% dimming driver for EcoSystem® controls
LDE5	Lutron EcoSystem® 5-Series 5% dimming driver for EcoSystem® controls
ELDO SOLOB	EldoLED Solodrive, 0.1% dimming driver for 0-10V controls
ELDO SOLOB DALI	EldoLED Solodrive, 0.1% dimming driver for DALI controls
ELDO ECO1	EldoLED Ecodrive, 1% dimming driver for 0-10V controls
ELDO ECO1 DALI	EldoLED Ecodrive, 1% dimming driver for DALI controls



FINISH OPTIONS

WHITE	BLACK	BRONZE	NICKEL	SILVER	ALUMINUM